

- Up to 6 auxiliary units can be connected to a master unit: Relay 1 and 2 on master unit; relays 3 to 8 on auxiliary units.


- Can have a mix of keypads & card reader units in one set

- Relay on every auxiliary unit that can be set via a dip switch. Keypad tones/ confirmation sound can be adjusted on

- DDA LEDS on each auxiliary unit indicates correct or

Units are wired via 5 cores of cat 5 cable.

incorrect code/card used.



Entrance 2




СОМ

All devices are connected to a master unit which has a built in transmitter.

Master K	leypad	Unit	
0j			
d d	0		
ad	a		ןת
a Aes	6		

Entrance 1

Entrance 3





card Reader Unit



auxiliary units.

up.

Now compatible with our AES PRO APP. With our pro app it's now easier to programme and have control over multiple units (sites) all from your mobile.

AES PR⊕

Technical Details			
Power	24v d.c		
Current	300mA/2A Peak 100mA Per Auxiliary Unit		
Weather Rating	IP55		
Relay Type	2 x N/C & N/O Contacts		
Total Permanent Keypad Codes	250		
Total Permanent Prox Cards	250		
Time Restricted Codes/Cards (Relay 1 only)	250		
Temporary Codes/Cards (Relay 1 only)	50		



Entrance 4

Auxiliary pedestal card reader & Keypad Unit










KEY-MST-PBPK-US Master unit with keypad & card reader.



KEY-MST-PBK-US Master unit with keypad.





KEY-MST-PBP-US Master unit with card reader.

Auxiliary **Pedestal** Keypads & Prox readers.




KEY-AUX-PBPK-US Aux pedestal unit with keypad & card reader.



KEY-AUX-PBK-US Aux pedestal unit with keypad.





KEY-AUX-PBP-US Aux pedestal unit with card reader.

Auxiliary Keypads & Prox readers.




KEY-AUX-IBPK-US Aux unit with keypad & card reader.



KEY-AUX-IBK-US Aux unit with keypad.





KEY-AUX-IBP-US Aux unit with card reader.

All black panels with textured powder coated aluminium hood and gloss black acrylic facia trim over a tough metal back plate. Keypad panels have a blue illuminated buttons.