



# e-KEYPAD

## SIMPLE AND SECURE

The e-Keypad offers a sleek access control solution, ideal for systems needing many codes. It features 3 unique channels and advanced settings for installers and supervisors. Integrates seamlessly with the e-LOOP range, allowing for a secure entrance and an easy exit.



CE

## FEATURES

- Quick installation with just 2 screws and no wiring.
- 433.39 MHz Transceiver.
- Waterproof housing.
- Operates from a single coin cell 2450 lithium battery.
- Can be unlocked and used as an entry button.
- Compatible with our e-LOOP transceivers.
- Store up to 200 user codes.
- Simple 4 to 8 pin code operation.
- Supervisor Code Storage: 1 Code.
- Establish codes that are valid for a limited number of uses.
- Voltage: 3V DC.
- Current draw standby: 200 nA.
- Peak current draw: 10 m/a.
- Battery type: CR2450.
- Battery type: 540 m/a.
- Frequency: 433.39 mHz.
- Channels: 3 Channels.
- Size: 5.1"H x 3.5"W x 0.7"D.
- Encryption: AES 128-Bit.

## EKPD-K KIT CONTENTS:

- 1 x e-Loop wireless e-Keypad.
- 1x e-trans-50 (Transceiver).